Subclause	Characteristic of Equipment	Manufacturer's Declared Values
	CONSTRUCTION	
	Model catalogue reference	UPS cabinet with number of BAT strings: Powerware 9155-20-N-0 Powerware 9155-20-N-xx-1-xxxxx-xxx Powerware 9155-20-N-xx-2-xxxxx-xxx Powerware 9155-20-N-xx-3-xxxxx-xxx Powerware 9155-20-N-xx-4-xxxxx-xxx Battery cabinets: Powerware 9X55-BAT-0 Powerware 9X55-BAT-1x24 Ah Powerware 9X55-BAT-2x24 Ah
	Model rating	20 kVA or 18 kW @ 230 Volts
	Classification	VFI-SS-111
MIL 217	MTBF	150 000 h
WIL 217	Dimensions length x depth x height	494 x 762 x 1684 mm (UPS) 494 x 758 x 1684 mm (battery cabinet)
	Weight without/with batteries	185 kg (UPS without batteries) 285 kg (UPS + 1 bat string) 385 kg (UPS + 2 bat strings) 485 kg (UPS + 3 bat strings) 585 kg (UPS + 4 bat strings) +15 kg (MBS option if selected)
	Weight without/with batteries	150 kg (empty) 510 kg (1 bat string) 870 kg (2 bat string)
	ENVIRONMENTAL	
4.1.4	Ambient storage temperature range	-25 to +55°C in the protective package
4.1.2	Ambient service temperature	Power electronics part: +0 to +45°C Battery part: +5 to +25°C without reducing the life time;
4.1.1	Maximum service altitude	1000 m (3300 ft) above sea level, max. 2000 m (6600 ft) with 1% derating per +100 m (330 ft)
4.1.3	Relative humidity range	5 to 95%, no condensation allowed
EN 60529	Degree of protection	IP20
7.3	Acoustic noise at 1 m - Normal mode - Stored energy	50 dBA 55 dBA
	ELECTRICAL CHARACTERISTIC	CS - INPUT
5.2.2 and 6.3.2.1	Rated input voltage and voltage tolerance	Rectifier input: 3x230/400 V nominal; <u>Tolerance:</u> 196/340-276/480 (-15%, +20%) at 100% load Bypass input: 230 V nominal; <u>Tolerance:</u> 196-253 V (-15%, +10%)
5.2.2 and 6.3.2.2	Rated input frequency and frequency tolerance	50 or 60 Hz, tolerance 45-65 Hz
5.2.2 and 6.3.10	Rated input current	28.1 A r.m.s (three phase input)
5.2.2 and 6.3.9.2	Maximum input current	56 A r.m.s (three phase input)
5.2.2	Input current distortion at rated input current	5% THD

Author: Teppo Henttonen Save date: 20.12.2006

File name: Technical Specification 9155-20 kVA

Page 1 of 4



Subclause	Characteristic of Equipment	Manufacturer's Declared Values
5.2.2 and 6.3.3	Inrush current	<100% of rated current
5.2.2	Number of input phases	3 Phases + N (three phase input)
	OUTPUT WAVEFORM	
5.3.1.2	Waveform – Normal mode	Sine waveform
5.3.1.2	Waveform – Stored energy mode	Sine waveform
	Transfer – Normal mode / Stored energy	No break
	Break time / make time	No break
ELECTRICAL OU	TPUT CHARACTERISTICS - STATIC CH	ARACTERISTICS - NORMAL MODE
5.3.2	Rated output voltage	220, 230 (default), 240 Vac
	Output voltage variation	± 2 V r.m.s / ± 1%
	Crest factor	3
	Rated output frequency (nominal)	50 (default) or 60 Hz
	• • • • • • • • • • • • • • • • • • • •	±2 (default), ±0.5, or ±1 Hz with slew
6.3.2.2	Output frequency variation (synchronised if applicable)	rate 1 Hz/s (default), 7 Hz/s, 3 Hz/s, 2 Hz/s, or ±0.5 Hz/s
6.3.2.3	Output frequency synchronised phase error at change of mode	Max. 8 degrees
	Rated output apparent power	20 kVA
	Rated output active power across linear load	18 kW
	Rated output active power across a reference (p.f. 0.7) non-linear load	14 kW
6.3.4.2	Total voltage distortion across a linear load	< 1%
6.3.8.1	Total voltage distortion across a reference non-linear load	< 5%
6.3.4.2	Individual harmonics voltage	See separate declaration
5.3.2 and 6.3.5.3	Short circuit capability	300 A, < 300 ms
		Without bypass: 10 min >100110% (29.7 kW) load 1 min >110125% (33.8 kW) load 5 sec >125150% (40.5 kW) load
5.3.2 and 6.3.5.1	Overload capability	With bypass: Continuous >100125% load 10 min >125150% load 5 ms 1000% load
		Note! Selected bypass fuses may limit the overload capability.
5.3.2 and 6.3.4	Range of load power factor permitted - linear load	0.7 lagging – 0.8 leading
	Number of output phases	1 Phase
5.3.2 and 6.3.4.5	Output voltage unbalance at reference unbalance load (multiphase only)	-
5.3.2 and 6.3.4.5	Maximum phase angle variation (multiphase only)	-
ELECTRICAL OUT	PUT CHARACTERISTICS - DYNAMIC CH	HARACTERISTICS - NORMAL MODE
5.3.2 and 6.3.6.1 and 6.3.6.2	Output voltage dynamic variation during transfer normal/stored energy	0%

Author: Teppo Henttonen Save date: 20.12.2006

File name: Technical Specification 9155-20 kVA

FATON

Powerware

Page 2 of 4

Subclause	Characteristic of Equipment	Manufacturer's Declared Values
6.3.7.1 and 6.3.8.4	Output voltage dynamic variation due to load changes	± 5% with 1 ms recovery (from 10% to 90% load step)
	Maximum rate of change of output frequency	0.5 (default), 2.5, or 7.5 Hz/s
ELECTRICAL OUT	PUT CHARACTERISTICS - STATIC CHA	RACTERISTICS - STORED ENERGY
5.3.1	Rated output voltage	220, 230 (default), 240 Vac
6.3.4.4	Output voltage variation	± 2 V r.m.s / ± 1%
	Crest factor	3
6.3.4.3	Rated peak output voltage	325 V
6.3.4.4	Rated peak output voltage variation	±20 V
0.0	Non-sinusoidal voltage rise time 0,1	
5.3.1.2	to 0,9 peak (if waveform exceeds 0,5 V/µs)	-
5.3.2	Output frequency	50 Hz (default) or 60 Hz
5.3.2	Output frequency variation	±0,005 Hz (single), ±0,07 Hz (parallel)
5.3.2	Rated output apparent power	20 kVA
5.3.2	Rated output active power	18 kW
5.3.2	Rated output active power non-linear load	18 kW
6.3.4.4	Total output voltage distortion	5% THD
6.3.4.4	Individual harmonic voltages - linear load	-
6.3.2 and 6.3.8.2	Individual harmonic voltages - non-linear load	-
5.3.2 and 6.3.5.4	Short circuit capability	300 A, <300 ms
5.3.2 and 6.3.5.2	Overload capability	10 min >100110% (29.7 kW) load 1 min >110125% (33.8 kW) load 5 sec >125150% (40.5 kW) load 300 ms >150% load
5.3.2	Range of load power factors permitted	0.7 lagging – 0.8 leading
5.3.2	Number of output phase (multiphase only)	1 Phase
ELECTRICAL OUTP	PUT CHARACTERISTICS - DYNAMIC CH	ARACTERISTICS - STORED ENERGY
	Output voltage dynamic variation	
6.3.6.1	during transfer from stored energy	0%
0.0.0.1	mode to normal mode	0.70
	Output voltage dynamic variation due	±5% with 1 ms recovery
6.3.7.1	to load changes	(from 10% to 90% load step)
	EFFICIENCY	
		93% at 100% rated load
6611	Efficiency Input / Output	92% at 75% rated load
6.6.11	Efficiency Input / Output	91% at 50% rated load
		86% at 25% rated load
	Heat dissipation	1440 W at 100% rated load
		1220 W at 75% rated load
		900 W at 50% rated load
	SYNCHRONIZATION (if appl	icable)

Author: Teppo Henttonen Save date: 20.12.2006

File name: Technical Specification 9155-20 kVA

FAT-N

Powerware

Page 3 of 4

Subclause	Characteristic of Equipment	Manufacturer's Declared Values			
6.3.2.2	Range of frequency synch	±2 (default), ±0.5, or ±1 Hz with slew rate 1 Hz/s (default), 7 Hz/s, 3 Hz/s, 2 Hz/s, or ±0.5 Hz/s			
6.3.6.4	Maximum phase error	8 degrees			
	5.4 STORED ENERGY MODE OF O	DPERATION			
	Duration of maximum permitted stored energy time at rated load	No limit.			
6.3.9.1	Stored energy time (for integral batteries) at rated load	See separate declaration			
	Restored energy time to 90% charge (for integral batteries)	Max. 10 h recommended			
6.3.9.2	Battery rating and quantity (for integral battery)	9 Ah and 36 units (VRLA), max. battery voltage 216*2.35V = 508 V			
	Battery recharge profile	ABM = 90% resting, 10% float charging			
6.3.9.1	Battery cut-off voltage	1.75 / 1.67 VPC			
5.8 CONTROL AND MONITORING SIGNALS					
5.8	See separate declaration for complete list of indications and remote alarm/monitoring or interface devices	See User's Manual			
	5.5.2 BYPASS CHARACTER	ISTICS			
5.5.2	Type of bypass	Manual and Automatic			
5.5.2	Mechanical/static	Mechanical Static			
5.5.2	No break transfer / break transfer	No break			
5.5.2	Break time / make time	No break			
5.5.2	Maintenance bypass	Yes (optional without)			
5.5.2	Bypass protection fuse or circuit- breaker rating	100 A			
5.5.2	Galvanic isolation fitted	No			
	5.7 ELECTROMAGNETIC COMPATIBILITY				
	Immunity, see IEC 62040-2	Yes			
	Emission, see IEC 62040-2	Yes			

Author: Teppo Henttonen Save date: 20.12.2006

File name: Technical Specification 9155-20 kVA

FATON

